

Wattmaster

THE BRAND ELECTRICIANS RELY ON

Intrinsically Safe Volt Stick

PART NO: WATVS660-642

FEATURES:

- Pocket sized non-contact voltage sensor with light indication
- Safely checks for the presence of AC voltage in cables, wall sockets, switches etc. without metal contact
- Locates breaks in cables and detects blown fuses
- Distinguishes between live and neutral wires in both single phase and three phase supply
- Safety hand guard prevents contact with dangerous cable
- Approved for use in explosive environment (IEC Ex NEM 07.0001)

TECHNICAL DATA:

Voltage range	230–1000V AC
Sensitivity	Indicates within 4mm of wire carrying 230V AC
Power supply	2 standard AAA batteries (included)
Category rating	CAT III 1000V AC
Approvals	Ex ib IIC T4, IEC 61010–1, IEC 900
Material	Radilon–S Hs (a), BE 170MO
Dimensions	151 x 18mm
Weight	40g



Note: This product requires an indent order form to be completed and returned before purchase order is placed.

Caution: Only to be used by a competent person. Prove on known live before and after testing. Does not detect voltage in all circumstances.

Wattmaster

THE BRAND ELECTRICIANS RELY ON

T: 1300 300 747 **F:** 1300 300 074

www.wattmaster.com.au